



LED converter 350 mA, on/off switchable

Article no. 17613000

Light.
For Generations.**Tender**

LED converter 350 mA, on/off switchable, , Rectangular. This driver fulfills the requirements for safety lighting systems in accordance with DIN EN 50172 VDE 0108-100:2005-01. This converter is equipped with safety devices which protect it against overvoltage, short-circuit as well as thermal and electric overloads. The input and output terminals are suitable for cables with a cross-section of up to 2.5 mm². Material: Plastic, Degree of protection: according to DIN EN 60529 IP20, Protection class: (EN 61140) II, Current: 350 mA, Voltage: 230V AC 50Hz, Power: 15 W, Dimmable: No, Control: on/off.

Article data	
Article no.	17613000
GTIN	4250047778721
Short description	LED converter 350 mA, on/off switchable
Material	Plastic
Shape	Rectangular
Length	115 mm
Width	34 mm
Height	19 mm
Scope of delivery	Plug&Play-Ausführung mit 110 mm P&P-Ausgangsleitung
Weight	0.067 kg
stamp	ENEC 05, EL

LED converter 350 mA, on/off switchable

Article no. 17613000

Light.
For Generations.

Operating technology of driver	
AC nominal voltage min	90 V
AC nominal voltage max	264 V
Frequency min	50 Hz
Frequency max	60 Hz
DC nominal voltage min	176 V
DC nominal voltage max	275 V
Output current	350 mA
Protection class	II
Degree of protection	IP20
max. no. lights on B16 A	27
Starting current	27 A (250 µs)
Power min	1 W
Power max.	15 W
Suitable for emergency lighting	No
Control	on/off
Environment temperature (ta)	0°C up to 40°C
Measure point (tc)	max. +75 °C
Version	Plug&Play

Packing data	
Gross weight	0.088 kg
Length of packaging	60 mm
Packaging width	27 mm
Packaging height	150 mm
Disposal at end of life	This product must not be disposed of with household waste. You are obliged, to dispose of such electrical waste separately. By disposing of electrical waste and other old or defective electronics separately, you support recycling or other forms of re-use. In that way you help to take care and to avoid that harmful substances get into the environment.