
BRUMBERG

LED converter 500 mA, DALI dimmable (digital)

Article no. 17826010

Light. For Generations.







Tender

LED converter 500 mA, DALI dimmable (digital), , Rectangular.This converter is equipped with safety devices which protect it against overvoltage, short-circuit as well as thermal and electric overloads. The input and output terminals are suitable for cables with a cross-section of up to 0.75-1.5 mm². Material: Plastic, Degree of protection: according to DIN EN 60529 IP20, Protection class: (EN 61140) II, Current: 500 mA, Voltage: 230V AC 50Hz , Power: 27 W, Dimmable: Yes, Control: DALI-2 .

Article data	
Article no.	17826010
GTIN	4251433924227
Short description	LED converter 500 mA, DALI dimmable (digital)
Material	Plastic
Shape	Rectangular
Length	146 mm
Width	44 mm
Hight	30 mm
Weight	0.154 kg
stamp	ENEC 05, MM, EL

All technical data as well as, weight and measurements are based on rated values and had been carefully prepared. We reserve the right to make technical changes which are are important in progressing. Product pictures are examples and can vary from the original. Subject to errors. Date 20.05.2024 Orders are placed under our general terms and conditions under https://www.brumberg.com/en/terms-and-conditions/general-terms-and-conditions-of-sale/

LED converter 500 mA, DALI dimmable (digital)

Article no. 17826010

Light. For Generations.

BRUMBERG

Operating technology of driver	
AC nominal voltage min	198 V
AC nominal voltage max	264 V
Frequency min	50 Hz
Frequency max	60 Hz
DC nominal voltage min	176 V
DC nominal voltage max	275 V
Output current	500 mA
Protection class	
Degree of protection	IP20
Starting current	5A 50µs
Power min	5 W
Power max.	27 W
Output_ripple_current	3
Suitable for emergency lighting	No
Control	DALI-2
Enviroment temprature (ta)	-25 °C up to +45 °C
Measure point (tc)	max. +85 °C
Version	without
Power factor	0.95

Packing data	
Gross weight	0.175 kg
Length of packaging	45 mm
Packaging width	35 mm
Packaging hight	190 mm
Disposal at end of life	This product must not be disposed of with household waste. You are obliged, to dispose of such electrical waste separately. By disposing of electrical waste and other old or defective electronics separately, you support recycling or other forms of re-use. In that way you help to take care and to avoid that harmful substances get into the environment.